


## 3.3V, Diagnostic Loopback, High Speed CAN Transceiver

### FEATURES

- Operates with a single 3.3V supply
- Compatible with ISO 11898-2 standard
- Bus pin ESD protection exceeds  $\pm 12\text{kV}$  HBM
- High input impedance allows for up to 120 nodes
- Adjustable driver transition times for improved emissions performance
- Low current standby mode:  $650\mu\text{A}$  typical
- Designed for data rates up to 1Mbps
- Thermal shutdown protection
- Open circuit fail-safe design
- Glitch free power up and power down protection for hot plugging applications

### PRODUCT APPEARANCE




Provide green and environmentally friendly lead-free package

### DESCRIPTION

The SL65HVD233 is the interface between the Controller Area Network (CAN) protocol controller and the physical bus. It is designed for use with the 3.3V  $\mu\text{Ps}$ , MCUs and DSPs with CAN controllers, or with equivalent protocol controller devices. It is used in industrial automation, control, sensors and drive systems, motor and robotic control, building and climate control (HVAC), telecom and base station control and status. The devices are intended for use in applications employing the CAN serial communication physical layer in accordance with the ISO 11898 standard.

PARAMETER	SYMBOL	CONDITION	MIN.	MAX.	UNIT
Supply voltage	$V_{cc}$		3	3.6	V
Maximum transmission rate	$1/t_{bit}$	Non-return to zero code	1		Mbaud
CANH, CANL input or output voltage	$V_{can}$		-36	+36	V
Bus differential voltage	$V_{diff}$		1.5	3.0	V
Virtual junction temperature	$T_j$		-40	125	$^{\circ}\text{C}$

**PIN CONFIGURATION**

**PINNING**

PIN	SYMBOL	DESCRIPTION
1	D	CAN transmit data input (LOW for dominant and HIGH for recessive bus states), also called TXD, driver input.
2	GND	Ground.
3	VCC	Transceiver 3.3V supply voltage.
4	R	CAN receive data output (LOW for dominant and HIGH for recessive bus states), also called RXD, receiver output.
5	LBK	Loopback mode input pin
6	CANL	Low level CAN bus line.
7	CANH	High level CAN bus line.
8	Rs	Mode select pin: strong pull down to GND=high speed mode, strong pull up to VCC=low power mode, 10kΩ to 100kΩ pull down to GND=slope control mode.

**LIMITING VALUES**

PARAMETER	SYMBOL	VALUE	UNIT
Supply voltage	V <sub>CC</sub>	-0.3~+6	V
DC voltage on D/R pins	D, R	-0.5~V <sub>CC</sub> +0.5	V
Voltage range at any bus terminal (CANH, CANL)	CANL, CANH	-36~36	V
Transient voltage on pins CANH, CANL (test with 100Ω) See <a href="#">Fig 10</a>	V <sub>tr</sub>	-40~+40	V
Receiver output current	I <sub>O</sub>	-11~11	mA
Storage temperature	T <sub>stg</sub>	-40~150	°C
Virtual junction temperature	T <sub>j</sub>	-40~125	°C
Welding temperature range		300	°C

The maximum limit parameters mean that exceeding these values may cause irreversible damage to the device. Under these conditions, it is not conducive to the normal operation of the device. The continuous operation of the device at the maximum allowable rating may affect the reliability of the device. The reference point for all voltages is ground.

**DRIVER ELECTRICAL DC CHARACTERISTICS**

SYMBOL	PARAMETER		CONDITION	MIN.	TYP.	MAX.	UNIT
$V_{O(D)}$	output voltage (Dominant)	CANH	$V_I=0V, R_S=0V, R_L=60\Omega$ ( <a href="#">Fig 1</a> , <a href="#">Fig 2</a> )	2.45		VCC	V
		CANL		0.5		1.25	
$V_{OD(D)}$	Differential output voltage (Dominant)		$V_I=0V, R_S=0V, R_L=60\Omega$ ( <a href="#">Fig 1</a> )	1.5	2	3	V
			$V_I=0V, R_L=60\Omega, R_S=0V$ ( <a href="#">Fig 3</a> )	1.2	2	3	V
$V_{O(R)}$	output voltage (Recessive)	CANH	$V_I=3V, R_S=0V, R_L=60\Omega$ ( <a href="#">Fig 1</a> )		2.3		V
		CANL			2.3		
$V_{OD(R)}$	Differential output voltage (Recessive)		$V_I=3V, R_S=0V$	-0.12		0.012	V
			$V_I=3V, R_S=0V,$ No load	-0.5		0.05	V
$I_{IH}$	High-level input current		$V_I=2V$	-30		30	$\mu A$
$I_{IL}$	Low-level input current		$V_I=0.8V$	-30		30	$\mu A$
$I_{OS}$	Short-circuit output current		CANH=-7V	-250			mA
			CANH=12V			1	
			CANL=-7V	-1			
			CANL=12V			250	
$C_O$	Output capacitance		See receiver				
$I_{CC}$	Supply current		Standby		650	950	$\mu A$
			$V_I=0V$ (Dominant), No load			6	mA
			$V_I=V_{CC}$ (Recessive), No load			6	mA

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^\circ C$ )

**DRIVER SWITCHING CHARACTERISTICS**

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$t_{PLH}$	Propagation delay time (low-to-high-level )	$R=0$ , Short circuit ( <a href="#">Fig 4</a> )		35	85	ns
		$R=10k\Omega$		70	125	
		$R=100k\Omega$		500	870	

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
<b>t<sub>PHL</sub></b>	Propagation delay time (high-to-low-level)	R=0, Short circuit ( <a href="#">Fig 4</a> )		70	120	ns
		R=10kΩ		130	180	
		R=100kΩ		870	1200	
<b>t<sub>sk(p)</sub></b>	Pulse skew (  t <sub>PLH</sub> - t <sub>PHL</sub>  )	R=0, Short circuit ( <a href="#">Fig 4</a> )		35		ns
		R=10kΩ		60		
		R=100kΩ		370		
<b>t<sub>r</sub></b>	Differential output signal rise time	R=0, Short circuit ( <a href="#">Fig 4</a> )	20		80	ns
		R=10kΩ	30		160	
		R=100kΩ	300		1400	
<b>t<sub>r</sub></b>	Differential output signal fall time	R=0, Short circuit ( <a href="#">Fig 4</a> )	20		80	ns
		R=10kΩ	30		160	
		R=100kΩ	300		1400	

(If not otherwise specified, V<sub>CC</sub>=3.3V±10%, Temp=T<sub>MIN</sub>~T<sub>MAX</sub>, Typical: V<sub>CC</sub>=+3.3V, Temp=25°C)

## RECEIVER ELECTRICAL CHARACTERISTICS

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
<b>V<sub>IT+</sub></b>	Positive-going input threshold voltage	<a href="#">Table 1</a>		750	900	mV
<b>V<sub>IT-</sub></b>	Negative-going input threshold voltage	<a href="#">Table 1</a>	500	650		mV
<b>V<sub>hys</sub></b>	Hysteresis voltage	V <sub>IT+</sub> - V <sub>IT-</sub>		100		mV
<b>V<sub>OH</sub></b>	High-level output voltage	-6V < V <sub>ID</sub> < 500mV I <sub>O</sub> = -8mA ( <a href="#">Fig5</a> )	2.4			V
<b>V<sub>OL</sub></b>	Low-level output voltage	900mV < V <sub>ID</sub> < 6V I <sub>O</sub> = 8mA ( <a href="#">Fig5</a> )			0.4	V
<b>I<sub>i</sub></b>	Bus input current	V <sub>IH</sub> = 12V, V <sub>CC</sub> = 0V	100		600	μA
<b>I<sub>i</sub></b>		V <sub>IH</sub> = 12V, V <sub>CC</sub> = 3.3V	100		500	μA
<b>I<sub>i</sub></b>		V <sub>IH</sub> = -7V, V <sub>CC</sub> = 0V	-450		-20	μA
<b>I<sub>i</sub></b>		V <sub>IH</sub> = -7V, V <sub>CC</sub> = 3.3V	-610		-30	μA
<b>R<sub>i</sub></b>	Bus input resistance	Corresponding standards of ISO 11898-2	20	35	50	kΩ

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$R_{diff}$	Differential input resistance	Corresponding standards of ISO 11898-2	40		100	k $\Omega$
$C_i$	Bus input capacitance	Corresponding standards of ISO 11898-2		40		pF
$C_{diff}$	Differential input capacitance	Corresponding standards of ISO 11898-2		20		pF

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

## RECEIVER SWITCHING CHARACTERISTICS

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$t_{PLH}$	Propagation delay time (low-to-high-level)	<a href="#">Fig 6</a>		35	60	ns
$t_{PHL}$	Propagation delay time (high-to-low-level)	<a href="#">Fig 6</a>		35	60	ns
$t_{sk}$	Pulse skew	$ t_{PHL} - t_{PLH} $			10	ns
$t_r$	Output signal rise time	<a href="#">Fig 6</a>		1.5		ns
$t_f$	Output signal fall time	<a href="#">Fig 6</a>		1.5		ns

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

## DEVICE SWITCHING CHARACTERISTICS

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$t_{(LOOP1)}$	Total loop delay, driver input to receiver output, recessive to dominant	R=0, Short circuit ( <a href="#">Fig 8</a> )		70	135	ns
		R=10 k $\Omega$		105	190	
		R=100 k $\Omega$		535	1000	
$t_{(LOOP2)}$	Total loop delay, driver input to receiver output, dominant to recessive	R=0, Short circuit ( <a href="#">Fig 8</a> )		70	165	ns
		R=10 k $\Omega$		105	190	
		R=100 k $\Omega$		535	1000	
$t_{(LBK)}$	Lookback delay, driver input to receiver output	<a href="#">Fig 9</a>		7.5	12	ns

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

## OVER TEMPERATURE PROTECTION

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$T_{j(sd)}$	Thermal shutdown temperature		155	165	180	°C

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

## CONTROL-PIN CHARACTERISTICS

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$T_{WAKE}$	wake-up time from standby mode	$R_S$ adds square wave (Fig7)		0.55	1.5	$\mu s$
$I_{RS}$	Input current for high-speed	$V_{RS}<1V$	-450		0	$\mu A$
$V_{RS}$	Input voltage for standby/sleep	$0<V_{RS}<V_{CC}$	$0.75V_{CC}$		$V_{CC}$	V
$I_{off}$	Power-off leakage current	$V_{CC}=0V$ , $V_{CANH}=V_{CANL}=5V$	-250		250	$\mu A$

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

## SUPPLY CURRENT

SYMBOL	PARAMETER	CONDITION	MIN.	TYP.	MAX.	UNIT
$I_{CC}$	Power consumption in standby mode	$R_S=V_{CC}$ , $V_I=V_{CC}$		650	950	$\mu A$
$I_{CC}$	Dominant power consumption	$V_I=0V$ , $R_S=0V$ , $LOAD=60\Omega$		50	70	mA
$I_{CC}$	Recessive power consumption	$V_I=V_{CC}$ , $R_S=0V$ , No load			6	mA

(If not otherwise specified,  $V_{CC}=3.3V\pm 10\%$ ,  $Temp=T_{MIN}\sim T_{MAX}$ , Typical:  $V_{CC}=+3.3V$ ,  $Temp=25^{\circ}C$ )

**FUNCTION TABLE**
**Table 1 Receiver characteristics in common mode ( $V_{(RS)}=1.2V$ )**

$V_{ID}$	$V_{CANH}$	$V_{CANL}$	R OUTPUT	
900mV	-6.1V	-7V	L	$V_{OL}$
900mV	12V	11.1V	L	
6V	-1V	-7V	L	
6V	12V	6V	L	
500mV	-6.5V	-7V	H	$V_{OH}$
500mV	12V	11.5V	H	
-6V	-7V	-1V	H	
-6V	6V	12V	H	
X	Open	Open	H	

(1) H=High level; L=Low level; X=Irrelevant.

**Table2.Driver Function**

INPUTS			OUTPUTS		
D	LBK	$R_s$	CANH	CANL	BUS STATE
X	X	$>0.75V_{CC}$	Z	Z	Recessive
L	L or Open	$<0.33V_{CC}$	H	L	Dominant
H or Open	X		Z	Z	Recessive
X	H	$0.33V_{CC}$	Z	Z	Recessive


(1) H= High level; L=Low level; Z=High impedance.

**Table3. Receiver Function**


INPUTS				OUTPUT
BUS STATE	$V_{ID}=CANH-CANL$	LBK	D	R
Dominant	$V_{ID} \geq 0.9V$	L or open	X	L
Recessive	$V_{ID} \leq 0.5V$ or open	L or open	H or Open	H
?	$0.5 < V_{ID} < 0.9V$	L or open	H or Open	?
X	X	H	L	L
X	X	H	H	H

(1) H=High level; L=Low level; ?=uncertain; X=Irrelevant.


**TEST CIRCUIT**




**Fig.1 Driver voltage, current and test definition**



**Fig.2 Bus logic state voltage definitions**



**Fig.3 Driver Vod test circuit**



- A、 The input pulse is supplied by a generator having the following characteristics: PRR≤500kHz, 50% duty cycle,  $t_r < 6\text{ns}$ ,  $t_f < 6\text{ns}$ ,  $Z_o = 50\Omega$ .
- B、  $C_L$  includes fixture and instrumentation capacitance, the error is within 20%.

**Fig.4 Driver test circuit and waveforms**

$$V_{IC} = \frac{V_{CANH} + V_{CANL}}{2}$$





Fig.5 Receiver voltage and current definitions



- A、 The input pulse is supplied by a generator having the following characteristics: PRR≤500kHz, 50% duty cycle,  $t_r < 6ns$ ,  $t_f < 6ns$ ,  $Z_o = 50\Omega$
- B、  $C_L$  includes fixture and instrumentation capacitance, the error is within 20%.

Fig.6 Receiver test circuit and waveform






Fig.7  $t_{(WAKE)}$  test circuit and waveform




The input pulse is supplied by a generator having the following characteristics: PRR≤125kHz, 50% duty cycle,  $t_r < 6ns$ ,  $t_f < 6ns$ ,  $Z_o = 50\Omega$ .

Fig.8  $t_{(LOOP)}$  test circuit and waveform



**Fig.9  $t_{(LBK)}$  test circuit and waveform**



**Fig.10 Overvoltage protection**

## ADDITIONAL DESCRIPTION

### 1 Sketch

The SL65HVD233 is the interface between the Controller Area Network (CAN) protocol controller and the physical bus. It is designed for use with the 3.3V  $\mu$ Ps, MCUs and DSPs with CAN controllers, or with equivalent protocol controller devices. It is used in industrial automation, control, sensors and drive systems, motor and robotic control, building and climate control (HVAC), telecom and base station control and status. It supports programmable data rates up to 1 Mbps. The devices are intended for use in applications employing the CAN serial communication physical layer in accordance with the ISO 11898 standard.

### 2 Current protection

A current-limiting circuit protects the transmitter output stage from damage caused by accidental short-circuit to either positive or negative supply voltage, although power dissipation increases during this fault condition.

### 3 Over temperature protection

SL65HVD233 has the function of over temperature protection. After the over temperature protection is triggered, the current of the driving stage will be reduced, because the driving tube is the main energy consuming part. The current reduction can reduce the power consumption and thus reduce the chip temperature. At the same time, other parts of the chip still work normally.

### 4 Transient protection

Electrical transients often occur in automotive application environment, CANH, CANL of SL65HVD233 have the function of preventing electrical transient damage.

### 5 Operating modes

The  $R_s$  pin mode, slop (pin 8) of the SL65HVD233 provides three different modes of operation: high-speed mode, slope-control mode, and low-power mode.

#### 5.1 High-Speed Mode

The high-speed mode can be selected by applying a logic low to the  $R_s$  pin (pin 8). The high-speed mode of operation is commonly employed in industrial applications. High-speed allows the output to switch as fast as possible with no internal limitation on the output rise and fall slopes. If the high-speed transitions are a concern for emissions performance slope control mode can be used.

If both high-speed mode and the low-power standby mode is to be used in the application, direct connection to a  $\mu$ P, MCU or DSP general purpose output pin can be used to switch between a logic-low level ( $<1.2V$ ) for high-speed operation, and the logic-high level ( $>0.75V_{CC}$ ) for standby.

#### 5.2 Slope Control Mode

Electromagnetic compatibility is essential in many applications while still making use of unshielded twisted pair bus cable to reduce system cost. Slope control mode was added to the SL65HVD233 devices to reduce the electromagnetic interference produced by the rise and fall times of the driver and resulting harmonics. These rise and fall slopes of the driver outputs can be adjusted by connecting a resistor from R<sub>S</sub> (pin 8) to ground or to a logic low voltage. The slope of the driver output signal is proportional to the pin's output current. This slope control is implemented with an external resistor value of 10kΩ to 100kΩ to achieve slew rate.


### 5.3 Standby Mode (Listen Only Mode)

If a logic high (>0.75VCC) is applied to R<sub>S</sub> (pin 8), the circuit of the SL65HVD233 enters a low-current, listen only standby mode, during which the driver is switched off and the receiver remains active. In this listen only state, the transceiver is completely passive to the bus. It makes no difference if a slope control resistor is in place. The μP can reverse this low-power standby mode when the rising edge of a dominant state (bus differential voltage >900mV typical) occurs on the bus. The μP, sensing bus activity, reactivates the driver circuit by placing a logic low (<1.2V) on R<sub>S</sub> (pin 8).

## 6 Diagnostic loopback function




The diagnostic loopback or internal loopback function of the SL65HVD233 is enabled with a high-level input on pin 5, LBK. This mode disables the driver output while keeping the bus pins biased to the recessive state. This mode also redirects the D data input (transmit data) through logic to the received data output pin, thus creating an internal loopback of the transmit to receive data path. This mimics the loopback that occurs normally with a CAN transceiver because the receiver loops back the driven output to the R (receive data) pin. This mode allows the host protocol controller to input and read back a bit sequence or CAN messages to perform diagnostic routines without disturbing the CAN bus.

If the LBK pin is not used it may be tied to ground (GND). However, it is pulled low internally (defaults to a low-level input) and may be left open if not in use.

**SOP8 DIMENSIONS**


**DIP8 DIMENSIONS**
**PACKAGE SIZE**


SYMBOL	MIN./mm	TYP./mm	MAX./mm
A	9.00	9.20	9.40
A1	0.33	0.45	0.51
A2	2.54TYP		
A3	1.525TYP		
B	8.40	8.70	9.10
B1	6.20	6.40	6.60
B2	7.32	7.62	7.92
C	3.20	3.40	3.60
C1	0.50	0.60	0.80
C2	3.71	4.00	4.31
D	0.20	0.28	0.36
L	3.00	3.30	3.60



**ORDERING INFORMATION**

TYPE NUMBER	PACKAGE	PACKING
SL65HVD233DR	SOP8	Tape and reel
SL65HVD233P	DIP8	Tube

SOP8 is packed with 2500 pieces/disc in braided packaging. DIP8 is packed with 50 pieces/tube in tube packaging.

**REFLOW SOLDERING**


Parameter	Lead-free soldering conditions
Ave ramp up rate ( $T_L$ to $T_P$ )	3°C/second max
Preheat time $t_s$ ( $T_{smin}=150^{\circ}\text{C}$ to $T_{smax}=200^{\circ}\text{C}$ )	60-120 seconds
Melting time $t_L$ ( $T_L=217^{\circ}\text{C}$ )	60-150 seconds
Peak temp $T_P$	260-265°C
5°C below peak temperature $t_p$	30 seconds
Ave cooling rate ( $T_P$ to $T_L$ )	6°C/second max
Normal temperature 25°C to peak temperature $T_P$ time	8 minutes max